Touch Screen Z Line Models Z6, Z9 & Z11 - EMV Restaurant Quick Reference Guide For SPIn Secure Payment Integration





** Note: Terminal Will Default at "POS ONLINE" Until Transaction is Initiated By POS System ** These steps have been provided as a guide for assistance.

CHIP CARD SALE	SWIPED OR MANUAL CARD SALE	DEBIT SALE
 Terminal "wakes up" & changes from POS Online Insert Chip Card Press OK to confirm Sale Amount Input TIP AMOUNT if prompted and press OK Terminal communicates with the Host Sign on Screen if applicable Receipts Print 	 Terminal "wakes up" & changes from POS Online Swipe OR Manually Enter Card # Press OK to confirm Sale Amount Input TIP AMOUNT if prompted and press OK If AVS prompts, input AVS information Terminal communicates with the Host Sign on Screen if applicable Receipts Print 	 Terminal "wakes up" & changes from POS Online Insert Chip Card When prompted tap "YES" Input PIN # on PIN Pad and press OK Press OK to confirm Sale Amount Input TIP AMOUNT if prompted and press OK Terminal communicates with the Host Sign on Screen if applicable Receipts Print
VOID TRANSACTION	RETURN TRANSACTION	SETTLE THE OPEN BATCH
 Terminal "wakes up" & changes from POS Online If prompted input Manager Password (1234 default) Receipts Print 	 Terminal "wakes up" & changes from POS Online If prompted input Manager Password (1234 default) Insert Chip Card Press OK to confirm Return Amount When applicable input PIN and press OK Terminal communicates with the Host Sign on Screen if applicable Receipts Print 	 From the POS ONLINE Screen tap the Favorites icons on the display: Tap CORE SETTLE DAILY BATCH If prompted input Manager Password (1234 default) Terminal communicates with the Host Settle Report Prints

Touch Screen Z Line Models Z6, Z9 & Z11 - EMV Restaurant Quick Reference Guide For SPIn Secure Payment Integration



** Note: Terminal Will Default at "POS ONLINE" Until Transaction is Initiated By POS System **

These steps have been provided as a guide for assistance.

SPIN BYPASS	WIRELESS ICON INDICATORS (MOBILE UNITS ONLY)	WI-FI ICON INDICATOR (FOR WI-FI ENABLED UNITS)
** Use these steps to process a stand alone transaction initiated from the payment device INSTEAD of the POS system. (le: POS is down) • From the POS ONLINE Screen tap the Favorites icons on the display: • Tap Turn SPIn Bypass On • Terminal Displays "Credit I Sale, Enter Amount" • You are now ready to process a stand along transaction at the terminal.	GPRS Signal Strength Indicator (The More Bars, The Better Your Signal GPRS) Battery Strength Indicator SIM Indicates Issue with SIM Card (GPRS)	Wi-Fi Not Connected Wi-Fi Connected Successfully
PRINTING REPORTS	EDIT TIPS ON TERMINAL	CALL ME FEATURE (MUST BE ENABLED)
 From the POS ONLINE screen press OK Tap REPORTS Tap Desired Report Type Input Password (1234 Default) and press OK Report Prints 	 From the POS ONLINE Screen tap the Favorites icons on the display: Tap Cr/Db Edit Tips Tap Desired Edit Method Add tip amount to desired transaction 	 From the POS ONLINE Screen tap the CALL ME icon on the display: Select "CALL ME" and press OK The terminal sends notification to the help desk and you will receive a call back from a representative with assistance.